

Handheld Oscilloscope

DSO/DMM/Generator/Counter/Analyzer

DSO8000 Series

Feature

- Five-in-one Handheld Oscilloscope:
Oscilloscope/DMM/ SpectrumAnalyzer/FrequencyCounter/Arbitrary Waveform generator.
- High Bandwidth 60MHz/100MHz/200MHz Oscilloscope, and 6000 Counts DMM.
- Arbitrary Waveform Generator: 25MHz arbitrary waveform output, 12 bits of vertical resolution.
- USB Host/Device 2.0 full-speed interface, RS-232/LAN Optional.

| Specification | | | | | | |
|---------------------------|--------------------------------|--|-----------------|----------|----------|----------------|
| | Model | DSO8202E | DSO8152E | DSO8102E | DSO8072E | DSO8060 |
| Horizontal | Channel | | | | 2 | |
| | Bandwidth | 200MHz | 100MHz | | 60MHz | |
| | Rise Time | ≤1.7ns | ≤3.5ns | | ≤5.8ns | |
| | Real-Time Sampling Rate | | 1GSa/s | | | 250MSa/s |
| | Equivalent Sampling Rate | | 25GSa/s | | | 50GSa/s |
| | Memory Depth | | 2M | | | 32K |
| Vertical | Time Base Range | 5ns/div~1000s/div | | | | |
| | Time Base Precision | ±50ppm | | | | |
| | Input Impedance | Resistance: 1M; Capacitance: 15pF | | | | |
| | Input Sensitivity | | 2mV to 100V/div | | | 10mV to 5V/div |
| Trigger | Input Coupling | AC, DC and GND | | | | |
| | Vertical Resolution | 8 bits | | | | |
| | Maximum Input | 400V (DC+AC Peak) | | | | |
| X-Y Mode | Source | CH1, CH2, EXT | | | | |
| | Mode | Edge, Pulse Width, Alternative, Video | | | | |
| Measurement | X-Axis Input | Channel 1 | | | | |
| | Y-Axis Input | Channel 2 | | | | |
| Meter Mode | Phrase Shift | Max. 3 degree | | | | |
| | Cursors | Manual: The difference between voltage cursors ΔV ; the difference between time cursors ΔT ; $1/\Delta T$ calculated by Hz.Tracing: The voltage and time at a waveform point | | | | |
| | Automatic | Pk-Pk, Max, Min, Mean, Cyc RMS, Frequency, Period, Rise Time, Fall Time, Positive Width,Negative Width | | | | |
| | Data Deal | CH+/-, CH2, CH1x CH2, CH1/CH2, FFT, Invert | | | | |
| | Internal Storage | 15 Waveforms and Setups | | | | |
| Signal Source Mode | Maximum Resolution | 6,000 Counts | | | | |
| | DMM Testing Modes | Voltage, Current, Resistance, Capacitance, Diode & Continuity | | | | |
| | Maximum Input Voltage | AC: 600V, DC: 800V | | | | |
| | Maximum Input Current | AC: 10A, DC: 10A | | | | |
| | Input Impedance | 10 MΩ | | | | |
| Measure Frequency Channel | Waveform Impedance | DC~25MHz | | | | |
| | DAC Clock | 2K~200MHz adjustable | | | | |
| | Frequency Resolution | 0.1% | | | | |
| | Channel Count | 1CH Waveform Output | | | | |
| | Waveform Depth | 4KSa | | | | |
| Other | Vertical Resolution | 12bit | | | | |
| | Frequency Stability | <30ppm | | | | |
| | Waveform Range | ±3.5V Max. | | | | |
| | Output Impedance | 50 Ω | | | | |
| | Output Current | 50mA, I peak=50mA | | | | |
| Other | System BW | 25M | | | | |
| | Harmonic Distortion | -50dBc(1KHz), -40dBc(10KHz) | | | | |
| | Frequency Range | DC~60MHz | | | | |
| | Input Range | 400mVpp~18Vpp | | | | |
| | Coupling Mode | DC | | | | |
| Other | Frequency Measurement Accuracy | ±Time Base Error ±1 Count | | | | |
| | Input Impedance | >100KΩ | | | | |
| | Type | Right angle 5.6", 16-digit color LCD | | | | |
| | Resolution | 640*480 dots | | | | 320*240 dots |
| | Contrast | 16 gears, with the progress bar to show adjustment | | | | |
| Other | Interface | USB host and USB slave, RS232/Lan Optional | | | | |
| | Voltage | DC Input:12~17VDC, 1500mA | | | | |
| | Size & Weight | 245 x 163 x 52 (mm); 1.3KG (exclusive of packing and accessories) | | | | |