



# PDR-301

Earth Testers / Earth resistance tester



## Basic Features

- Phase detection system circuit for stable measurement
- Easy self calibration
- AC 30V range to avoid indication errors caused by leak current
- Power saving design with push switch
- Exorbitance warning LED of auxiliary earth electrode resistance

## Optional Accessories

Carrying case : C-PDR300

## Specifications

PDR-301	
Earth resistance measuring range	10/100/1000Ω Accuracy : X1 range ±5% of full scale : X10, X100 range ±2.5% of full scale
Earth resistance measuring range	0~30V Accuracy ±2.5% of full scale
Display	Analog
Operation	Constant current system (tripolar or bipolar)
Battery	R6P×6
Size / Mass	W175×H118×D55mm/Approx. 500g
Standard accessories included	Earth bar set (SET-PDR201), Instruction manual